

# Markdown Demo

(Using ZBI)





## Overview

This demo allows you to pair your RS507 Bluetooth® ring scanner with a QLn320 printer and print markdown labels. As barcodes are scanned the data is processed by the ZBI application which determines if a label is printed or not.

The demo also shows [customized menus](#) can be created and used on the front panel of the printer.

Equipment:	Software tools & configuration files:
<ul style="list-style-type: none"><li>QLn320 dual radio version with ZBI enabled.</li><li>2" x 1" labels.</li><li>RS507 Ring Scanner.</li></ul>	<ul style="list-style-type: none"><li><a href="#">PC Tool for RS507</a></li><li><a href="#">Zebra Setup Utilities</a></li><li><a href="#">Printer Configuration Files</a></li></ul>



## RS507 Scanner Configuration

1	Scan Defaults	 <b>*Set Defaults</b>
2	Scan SPP barcode	SPP bar code 
3	Scan Pairing barcode for your printer.	Generate this barcode using the PC tool for RS507 application.

# Markdown Demo

(Using ZBI)



4	Scan the reconnect on Power up barcode	<p>On power up</p> 
5	Scan <DATA><SUFFIX1>	 <p>&lt;DATA&gt; &lt;SUFFIX 1&gt; (01h)</p>
6	Power cycle the Ring scanner by removing/replacing the battery.	
7	After the scanner has re-paired with the printer, restart the ZBI app on the printer using the RESET menu option.	


# Markdown Demo

(Using ZBI)




## Demo Installation:

1. Ensure ZBI is enabled on your printer. If necessary obtain a license and enable ZBI on your printer. See [this support article](#) for information on how enable ZBI or check if ZBI is enabled on your printer.
2. Download the **Printer Configuration File** from the link on page 1. Send the file to the printer. The printer should reboot and eventually wait for the scanner to connect as shown in the image below.  
(Note: 'App not running' will be displayed during start up).



3. Power cycle the scanner. Once it's paired with the printer, the main menu will be displayed.



4. See instructions on the following pages on how to use the demo.
5. If the printer continually displays 'App not running' check ZBI is enabled.

## How to remove the demo from your printer:

1. Download the **Printer Configuration Removal File** from the link on page 1.
2. Send the file to the printer. The printer should reboot and power up with the default menu.


# Markdown Demo

(Using ZBI)



## To print a markdown label:

1. Scan any UPC (12 digit) or EAN (13 digit) barcode on any product or use the sample barcodes on the next page.
  - a. UPC/EAN Barcodes with first digit **greater** than 4 will cause a markdown label to print and the display to indicate a price change.



- b. UPC/EAN Barcodes with first digit 4 or lower will cause the display to show 'NO CHANGE'.
  - c. INVALID UPC will be displayed for barcodes scanned with incorrect data length.
2. Use the setup menu option to select the currency symbol to print – British Pound, Euro or U.S. Dollar.

## Sample Barcodes

